# DG95 · 96 · 97 · 98 Differential Pressure Gauge

# Overview

This compact differential pressure gauge can measure other various measuring units other than pressure to monitor level or flow measurements. Switch can also be equipped for alarm or pressure control application.

# Features

- Selectable upper connection mounting or lower connection mounting available for easy installation
- •Since lead switch is used, switch action part is not influenced by external environment with long life and high reliability (DG97•98).
- Certified by the Minister of Trade and Industry type available (Option)



\*Reference pressure is the pressure to reference, or less fluctuating pressure side. Proof pressure against single port means the maximum over differential pressure.

# Specifications 1

# Model:

DG95 · 96 General fine differential pressure gauge DG97 · 98 Fine differential pressure switch

## Media:

Gases or liquids

# Operating environment:

Install in location where no gases or liquids may exist that have the potential to become flammable or ignitable under normal operating condition (for DG97  $\cdot$  98)

## Mounting:

DG95 · 96 2B pipe, wall mounting (Zero adjustment screw, air vent, filter) DG97 · 98 2B pipe, wall mounting (Zero adjustment screw, air vent, filter)

## Size:

DG95 · 97 φ 100 DG96 · 98 φ 150

# Connection:

Rc1/4, 1/4NPT Female

# Wetted parts:

Pressure container SCS14
Bellows SUS316L
Gasket NBR

# Differential pressure range:

0 to 5kPa → 0 to 1MPa

# Reference pressure:

0 to 5MPa

# Proof pressure for single port:

0.2 to 1.2MPa (Varies depending on pressure ranges)

# Operating temperature range:

-5 to 40°C (Non-freezing)

# Accuracy:

±1.5%F.S.

( $\pm 2\%$ F.S. for 10kPa and below (DG97 • 98))

# Case material · finish:

ADC12 · Black

# Manifold valve: (Option)

Three-way valve in combination with stop valve both for high and low pressure, and equalizing valve. It prevents from overpressure, reversed pressure during zero point monitoring, zero adjustment operation or when the process starts its operation.

## Custom dial: (Option)

Custom letters, colored circle and customer's logo

## Weight:

Approx. 2.9kg to 4.3kg

# Differential Pressure Gauge

# Specifications 2

## Minimum scale:

Differential pressure range	Proof pressure for single port	Minimum scale
0 to 5kPa	0.2MPa	0.1kPa
0 to 7		0.2
0 to 10		0.2
0 to 15		0.5
0 to 20		0.5
0 to 30	0.4MPa	1
0 to 40		1
0 to 50		1
0 to 70		2
0 to 100		2
0 to 200		5
0 to 300	1.2MPa	10
0 to 400		10
0 to 600		20
0 to 1MPa		20

# Electrical rating (DG97 • 98):

Switch	Rating	Withstand voltage	Insulation resistance			
Lead switch	125V AC 0.2A 200V DC 0.25A 100V DC 0.7A (Load resistance)	Between non-continuous terminal strip 400V AC 1 minute Between terminal and case 600V AC 1 minute	500V DC 100MΩ and above Between each terminal and case			
Note						

•Ensure the use of protection circuit when capacity load, lamp or long cable are in use carrying inductive load or surge current (Inrush current).

# Specifications for DG97.98 pressure switch

Setting accuracy:

±2%F.S.

Repeatability:

±1%F.S.

Deadband:

Fixed 5%F.S. and below

Temperature coefficient:

±0.05%F.S./℃

Switch:

Lead switch

Number of contacts:

One contact or two contacts

Setting method:

Internally adjustable

Electrical wire outlet:

Conduit type G3/4, G1/2, Rc1/2, 1/2NPT


Gland JIS 20b


# Dimensions 1

DG95 · 96


Unit: mm








# Back connection





	+	1	
4×M5	26.5	fro	13.5
Depth 6	View		om A

Model	D1	D2	Dз	D4	а
DG95	128	109	102	119	21
DG96	178	159	152	169	23.5

\*Upper or lower mounting side works for air vent when the other one is in use.


<sup>·</sup>Not available for 200V AC use


# Differential Pressure Gauge

# Dimensions 2 DG97 · 98


Unit: mm








# Wall mount






Model	D	е	а	b	С
DG97	109	80	46.5	71.5	112.5
DG98	159	104	49	74	115


air vent when the other one is in use.

# Manifold valve: (Option)



┌ FV42-99<u>3</u> ┐






# Switch action and wirings

# DG97 • 98 Differential pressure switch

Model	Switch action	Mark	Diagram of switch action	Wiring terminal number	Setting pointer
DG97 DG98	Upper limit with one contact (Reversed lower limit with one contact)	H (LR)	When differential pressure goes up (down) and reaches at set point, switch operates and turn circuit ON (OFF).  Upward pressure →  OFF ON  O SET max.	1 - 2	Red pointer
	Lower limit with one contact (Reversed upper limit with one contact)	L (HR)	When differential pressure goes down (up) and reaches at set point, switch operates and turn circuit ON (OFF).  ←Downward pressure  ON OFF  0 SET max.	3 – 4	Yellow pointer
	Upper and lower limit with two contacts (Reversed upper and lower limit with two contacts)	HL (HRLR)	Independently operates with combination of upper limit (reversed lower limit) and lower limit (reversed upper limit).		Red pointer Yellow pointer
	Upper limit with two contacts (Reversed lower limit with tw contacts)	2H (2LR)	Independently operates with combination of upper limit (reversed lower limit) with two contacts.	① - ② ③ - ④	Red pointer Yellow pointer
	Lower limit with two contacts (Reversed upper limit with one contacts)	2L (2HR)	Independently operates with combination of lower limit (reversed upper limit) with two contacts.	① - ② ③ - ④	Red pointer Yellow pointer


**Model number configuration** Please specify the model, each requiring specification and differential pressure range to order.



[Note 1] Custom dial: Custom letters, colored circle and customer's logo

- · Zero adjustment screw, air vent, filter
- As setting scale on dial includes setting error, ensure the use of master gauge and reference pressure gauge to maintain accurate setting.
- \*Specify code "X" to refer N/A

**Model number configuration** Please specify the model, each requiring specification and differential pressure range to order.



OAs setting scale on dial includes setting error, ensure the use of master gauge and reference pressure gauge to maintain accurate setting.

\*Specify code "X" to refer N/A